

# *This is your best LED Lighting Solution... Period.*



- High Efficiency, Long Lasting
- 3 Year Warranty
- Direct Incandescent Replacement
- Fast Turn On, No Warm-up
- Choice of Kelvin Temps\*
- Multi-Voltage 100-280 Volts

## INTRODUCING THE **LED Corncob Lights**

*If you find something better... buy it!  
It's that Simple!*



**AAMSCO LIGHTING, INC.**  
100 Lamp Light Circle • Summerville, SC 29483  
1-800-221-9092 • Fax 843-278-0001 • [www.aamsco.com](http://www.aamsco.com)



## LED Corncob Light

MODEL #	DESCRIPTION
<b>LED12W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 62mm, Length 130mm</li> <li>3. Base: Medium</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 13W</li> <li>6. LED Source: 180pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 1150lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 36W CFL</li> </ol>
<b>LED15W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 73mm, Length 150mm</li> <li>3. Base: Medium or Mogul</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 17W</li> <li>6. LED Source: 216pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 1600lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 100W incandescent</li> </ol>
<b>LED20W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 90mm, Length 196mm</li> <li>3. Base: Medium or Mogul</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 23W</li> <li>6. LED Source: 330pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 2000lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 150W incandescent</li> </ol>
<b>LED30W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 90mm, Length 204mm</li> <li>3. Base: Medium or Mogul</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 33W</li> <li>6. LED Source: 510pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 3100lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 200W incandescent</li> </ol>
<b>LED40W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 90mm, Length 230mm</li> <li>3. Base: Medium or Mogul</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 44W</li> <li>6. LED Source: 660pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 4000lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 300W incandescent</li> </ol>
<b>LED60W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 90mm, Length 292mm</li> <li>3. Base: Medium or Mogul</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 67W</li> <li>6. LED Source: 960pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 6000lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 500W incandescent</li> </ol>
<b>LED80W</b>	<ol style="list-style-type: none"> <li>1. Beam angle: 360 degrees</li> <li>2. Size: Diameter 105mm, Length 290mm</li> <li>3. Base: Medium or Mogul</li> <li>4. Rated Voltage: 100–300V, 50/60Hz</li> <li>5. Power consumption: 88W</li> <li>6. LED Source: 1160pcs LEDs</li> <li>7. Color temperature: 2700–6700K</li> <li>8. Luminous Flux: 8500lm</li> <li>9. Lifetime: 50,000 Hours</li> <li>10. Recommended replacement for 750W incandescent</li> </ol>

- Integrated Heat-Sink Design
- 3 Year Warranty
- Sturdy PCB housing
- High CRI with great directionality. Ideal for warehouse, indoor lighting, and street lamps.
- 80% more energy saving compared with conventional street lights, CFL, and incandescent light.